

Baby Tuner

Tuner Pedal

Owner's Manual

Precautions

PLEASE READ CAREFULLY BEFORE PROCEEDING

Power Supply

Please connect the designated AC adapter to an AC outlet of the correct voltage. Please be sure to use only an AC adapter which supplies 9V (±10%) DC, center minus. The maximum working voltage shall not exceed 12V, otherwise may be dangerous equipment damage, fire or other problems. Unplug the AC power adapter when not using or during electrical storms.

Connections

Always turn off the power of this and all other equipment before connecting or disconnecting, this will help prevent malfunction and / or damage to other devices. Also make sure to disconnect all connection cables and the power cord before moving this unit.

Cleaning

Clean only with a soft, dry cloth. If necessary, slightly moisten the cloth. Do not use abrasive cleanser, cleaning alcohol, paint thinners, wax, solvents, cleaning fluids, or chemical-impregnated wiping cloths.

Interference with other electrical devices

Radios and televisions placed nearby may experience reception interference. Operate this unit at a suitable distance from radios and televisions.

Location

To avoid deformation, discoloration, or other serious damage, do not expose this unit to the following conditions:

- Direct sunlight
- Heat sources
- Magnetic fields
- Extreme temperature or humidity
- Excessive dusty or dirty location
- High humidity or moisture
- Strong vibrations or shocks

FCC certification


This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- This device may not cause harmful interference.
- This device must accept any interference received, including interference that may cause undesired operation.

Main Features

- A high precision tuning micro pedals, can be accurate to ±1 points
- Works with most Electric or Electro-Acoustic instruments including seven string guitar or five string bass
- Display Uses 108 high brightness LED's and is visible even in strong light/sun
- Very small and compact design
- True bypass switch
- DC 9V adapter power supply

Panel Instruction



- 1. TRUE BYPASS Footswitch:**
Push down the footswitch to toggle between on and true bypass status.
- 2. DC IN Power Jack:**
For power supply, use a 9-volt DC regulated AC adapter (plug polarity is positive on the barrel and negative in the center).
- 3. INPUT Jack:**
1/4" mono audio jack, for connecting guitar.
- 4. OUTPUT Jack:**
1/4" mono audio jack, outputs the signal.
- 5. NOTE Display:**
Displays the note read with sharps in upper right.
- 6. FINE TUNING Display:**
The blue indicator light and the auxiliary lights on both sides will show together once tuning is correct.

Operating instructions

- Press the Baby Tuner ON/OFF switch to activate the tuner, the panel light is lit up at this time, for the mute state
 - While tuning, "--" will show on when there is no signal input, but the musical alphabet note indicator and fine-tuning indicator will shine together once there is signal input
 - When correctly tuned, the blue middle indicator light and the red lights on both sides will show on together
- * **Note:** When not tuning status, the signal is true bypass, screen doesn't display

Specification

Detection range: 12Hz ~ 4186Hz (C8)

Input: 1/4" monaural jack

Output: 1/4" monaural jack

Power Requirements: AC adapter 9V DC (center minus plug), recommended to use Moorer Micro Power

Current Draw: 90 mA

Dimensions: 93.5mm (D) × 42mm (W) × 52mm (H)

Weight: 140g

Accessories: Owner's Manual

Disclaimer: Any specification's update won't be amended in this manual.